

3-Screen Display

New

Multi-channel Digital Sensor Monitor

Up to 4 pressure sensors can be connected!



It is possible to change the settings while checking the measured value.

Main screen Measured value (Current pressure value)

Sub screen Left side: Label (Display item), Right side: Set value (Threshold value)

Visualization of Settings

| | |
|-----------------------------|------|
| Set value (Threshold value) | P.1 |
| Hysteresis value | H.1 |
| Peak value | H.H. |
| Bottom value | H.Lo |
| Channel display | CH.1 |

- Differential Pressure Check Mode [p.2](#)
- 3 channels are displayed simultaneously. [p.2](#)
- Input Range Selection [p.3](#)

IO-Link Compatible • Hub Function [p.4](#)
Convert analog signals to digital signals!



Applicable Pressure Sensor Variations

Compact Pneumatic Pressure Sensor PSE53□



Compact Pneumatic Pressure Sensor PSE54□



Low Differential Pressure Sensor PSE550



Pressure Sensor for General Fluids PSE56□



Pressure Sensor for General Fluids PSE57□




PSE200A Series



CAT.ES100-124A (A)

Visualization of Settings

Item and set value are displayed together. Easy to confirm the displayed item




Mode Examples

| Mode | Item | Set value (Threshold value) | Item | Set value (Threshold value) | Item | Set value (Threshold value) | | |
|-----------------|------------------------|-----------------------------|------------------------|-----------------------------|--------------------------|-----------------------------|--------------------------|------|
| Hysteresis mode | Normal output | -505 | Reversed output | -505 | Hysteresis | 51 | | |
| | Normal output/ Lo side | -300 | Normal output/ Hi side | -600 | Reversed output/ Lo side | -300 | Reversed output/ Hi side | -600 |

Easy Screen Switching

It is possible to change the settings while checking the measured value.



The sub screen can be switched by pressing the down buttons.


* One additional arbitrary display mode can be added via the function settings.

- CH display
- Other channel
- Customer defined label
- Level bar

Simple 3-Step Setting

After selecting the channel, when the SET button is pressed and the set value (P_1) is displayed, the set value (threshold value) can be set.



When the SET button is pressed and the hysteresis (H_1) is being displayed, the hysteresis value can be set.



Now with a snap shot function for set value reading


Snap shot function Pressing the **▲** and **▼** buttons simultaneously for a minimum of 1 second will make the set value (threshold value) the same as the current pressure value.

Centralized Control Saves Installation Space.





Differential Pressure Check Mode p. 16



One monitor displays 2 lines of differential pressure.




A Single Monitor Various Applications



3 channels are displayed simultaneously.
 (Customer defined channel can be set.)



Input Range Selection (for Pressure/Flow rate)



The sensor input range can be set to the required value and displayed. (Voltage input: 1 to 5 V)
Pressure switch/Flow switch can be displayed.

A is displayed for 1 V. B is displayed for 5 V.

The range can be set as required.

Refer to page 8 for the specification of the sensors which can be connected.

For the individual specifications of each connectable sensor, refer to the **Web Catalog**.

For Digital Flow Switch for Water / PF3W511



| | A | B |
|---------|---|-----|
| PF3W504 | 0 | 4 |
| PF3W520 | 0 | 16 |
| PF3W540 | 0 | 40 |
| PF3W511 | 0 | 100 |

Set A and B to the values shown in the table on the left.

For Flow Sensor / PFMV5




Setting of the display for analog voltage

| | A | B |
|--------------|------|------|
| PFMV5 Series | 1.00 | 5.00 |

Set A and B to the values shown in the table on the left.

Connectors

Connection and removal of wiring is easy.



Functions pp. 14 to 17

Auto-preset function

This function, when selected in the initial setting, calculates and stores the set value from the measured pressure.

Display value fine adjustment function

Fine adjustment of the indicated value of the pressure sensor can be made within the range of $\pm 5\%$ of the read value.

Peak/Bottom value indication function

This function constantly detects and updates the maximum (minimum) pressure when the power is supplied, and allows to hold the maximum (minimum) pressure value.

Key-lock function

This function prevents operation errors such as accidentally changing setting values.

Zero-clear function

This function clears and resets the zero value on the display of measured pressure.

Error display function

This function displays error location and content when a problem or error has occurred.

Anti-chattering function

This function prevents the detection of such temporary drops in the supply pressure as errors by changing the delay time setting.

Pressure range/Unit selection function

The pressure range and displayed unit can be switched.

Zero-cut setting

When the pressure display value is close to zero, this function forces the display to zero.

Selection of power-saving mode

Power-saving mode can be selected. It shifts to power-saving mode automatically when there is no button operation for 30 seconds.

Setting of security code

Users can select whether a security code must be entered to release the key lock.

Auto-shift function

This function compensates for such supply pressure fluctuations. It measures the pressure at the time of auto-shift signal input and uses it as the reference pressure to correct the set value on the switch.

Differential pressure check mode

Set and display the differential pressure between CH1 - CH2, and CH3 - CH4.

Channel to channel copy function

The set values can be copied to other channel.

Channel select function

Pressure value for the selected channel is displayed.

Channel scan function


Pressure values for each channel are displayed in turn every 2 seconds.

Hub Function

Converts analog signals to digital signals and supports IO-Link

A currently used sensor can be used.

* Supports analog voltage output 1-5 V



Process Data

| | | | | | | | | | | | | | | | | | |
|------------|---|----|-------------|----|----|---------------|---------------|---------------|---------------|----------|----------|----------|----------|----------|----------|----------|----------|
| Bit offset | 79 | 78 | 77 | 76 | 75 | 74 | 73 | 72 | 71 | 70 | 69 | 68 | 67 | 66 | 65 | 64 | |
| Item | CH1*1 measured value: 16-bit signed integer | | | | | | | | | | | | | | | | |
| Bit offset | 63 | 62 | 61 | 60 | 59 | 58 | 57 | 56 | 55 | 54 | 53 | 52 | 51 | 50 | 49 | 48 | |
| Item | CH2 measured value: 16-bit signed integer | | | | | | | | | | | | | | | | |
| Bit offset | 47 | 46 | 45 | 44 | 43 | 42 | 41 | 40 | 39 | 38 | 37 | 36 | 35 | 34 | 33 | 32 | |
| Item | CH3*2 measured value: 16-bit signed integer | | | | | | | | | | | | | | | | |
| Bit offset | 31 | 30 | 29 | 28 | 27 | 26 | 25 | 24 | 23 | 22 | 21 | 20 | 19 | 18 | 17 | 16 | |
| Item | CH4 measured value: 16-bit signed integer | | | | | | | | | | | | | | | | |
| Bit offset | 15 | 14 | 13 | 12 | 11 | 10 | 9 | 8 | 7 | 6 | 5 | 4 | 3 | 2 | 1 | 0 | |
| Item | Error diagnosis | | Reservation | | | CH4 diagnosis | CH3 diagnosis | CH2 diagnosis | CH1 diagnosis | CH4 OUT2 | CH4 OUT1 | CH3 OUT2 | CH3 OUT1 | CH2 OUT2 | CH2 OUT1 | CH1 OUT2 | CH1 OUT1 |

Measurement data of sensors for 4 channels are combined and cyclically sent as a process data.

Each channel has 2 outputs*3.

| | | | |
|----------------|--------------------------------|----------------|---|
| Diagnosis item | · Internal product malfunction | Diagnosis item | · Applied pressure error |
| | · Outside of zero-clear range | | · Differential pressure measurement error |


Implement diagnostic bits in the process data.

*1 During differential pressure operation mode, CH1-CH2 measurement value is used.
 *2 During differential pressure operation mode, CH3-CH4 measurement value is used.
 *3 During SIO mode, only CH1 has 2 switch outputs. CH2-4 has one output each.

IO-Link


IO-Link is an open communication interface technology between the sensor/ actuator and the I/O terminal that is an international standard, IEC61131-9.

Visualization of operation/equipment status Remote monitoring and control by communication




Automatic setting function [Data storage function]

When replacing the sensor monitor with the same type (the same device ID), the parameters (set values) stored in the IO-Link master are automatically copied (set) to the new sensor monitor.



Displays the output communication status and indicates the presence of communication data




Operation and Display

| Communication with master | IO-Link status indicator light | Status | Screen display #2 | Description | |
|---------------------------|--------------------------------|----------|-----------------------------|------------------------------------|--|
| Yes | *1 | Normal | Operate | Mode oPE | Normal communication status (readout of measured value) At the start of communication |
| | | | Start up | Mode Start | |
| | | | Preoperate | Mode Pre | |
| No | *1 (Flashing) | Abnormal | Version does not match | Er 15 V 1.0 | IO-Link version does not match that of the master. The master uses version 1.0. * The applicable IO-Link version is 1.1. |
| | | | Communication disconnection | Mode oPE Mode Start Mode Pre | |
| | OFF | SIO mode | Mode Sio | General switch output | |






*1 In IO-Link mode, the IO-Link indicator is ON or flashes. *2 When the sub screen is set to Mode
* "ModE LoC" is displayed when the data storage lock is enabled. (Except for version mismatch or when in SIO mode)

Series Variations



| | | | | |
|-----------------------------|---------------------------|---------------------|--------------|------------------------|
| Basic Specifications | Repeatability | ±0.1% (F.S.) | ±0.1% (F.S.) | |
| | Voltage | 12 to 24 VDC | 12 to 24 VDC | |
| | No. of outputs for switch | 5 outputs | 2 outputs | |
| | Analog output | — | — | 1 to 5 V 4 to 20 mA |
| | Operating temperature | 0 to 50°C | 0 to 50°C | |

| | | | | |
|------------------|-------------------|--|-----------|------|
| Functions | Number of screens | 3 | 3 | |
| | Enclosure | Front face: IP65 Others: IP40 | IP65 | IP40 |
| | 3 Step | Yes | Yes | |
| | Wiring | Connector | Connector | |


| | | | | | | |
|------------------------------------|--|--|--|---|---|---|
| Applicable Pressure Sensors | Refer to the Web Catalog for details. | Compact Pneumatic Pressure Sensor PSE53□  | Compact Pneumatic Pressure Sensor PSE54□  | Low Differential Pressure Sensor PSE550  | Pressure Sensor for General Fluids PSE56□  | Pressure Sensor for General Fluids PSE57□  |
| | | Rated pressure range | Rated pressure range | Rated pressure range | Rated pressure range | Rated pressure range |
| | | -101 kPa to 0 | -101 kPa to 0 | 0 to 2 kPa | -101 kPa to 0 | -100 kPa to 100 kPa |
| | | -100 kPa to 100 kPa | -100 kPa to 100 kPa | | -100 kPa to 100 kPa | 0 to 500 kPa |
| | | 0 to 100 kPa | 0 to 1 MPa | | 0 to 500 kPa | 0 to 1 MPa |
| | | 0 to 1 MPa | | | 0 to 1 MPa | 0 to 2 MPa |
| | | | | 0 to 5 MPa | | |
| | | | | 0 to 10 MPa | | |

CONTENTS

| | | | |
|-----------------------------------|------|---|-------|
| How to Order | p. 7 | Internal Circuits and Wiring Examples | p. 9 |
| Options/Part Nos. | p. 7 | Dimensions | p. 12 |
| Specifications | p. 8 | Function Details | p. 13 |
| Applicable Pressure Sensors | p. 9 | | |

3-Screen Display Multi-channel Digital Sensor Monitor

PSE200A Series



How to Order

PSE20 **0** A - **M**

Input/Output specification

| | |
|----------|---|
| 0 | NPN 5 outputs + Auto-shift input |
| 1 | PNP 5 outputs + Auto-shift input |
| 2 | IO-Link + NPN 4 outputs or NPN 5 outputs (SIO mode) |
| 3 | IO-Link + PNP 4 outputs or PNP 5 outputs (SIO mode) |

Unit specification

| | |
|------------|--------------------------------|
| Nil | With unit selection function*1 |
| M | SI units only*2 |

- *1 Under the New Measurement Act, switches with the unit selection function are no longer allowed for use in Japan.
- *2 Fixed unit: kPa, MPa, Pa

Option 1

| | |
|------------|--|
| Nil | None |
| A | Panel mount adapter ZS-26-B Waterproof seal (Accessory) Tapping screw (3 x 8L) (Accessory) Panel mount adapter Panel |
| | Front protection cover + Panel mount adapter ZS-26-C Front protection cover ZS-26-01 (Accessory) Waterproof seal (Accessory) Tapping screw (3 x 8L) (Accessory) Panel mount adapter Panel |

* Options are not assembled, but shipped together.

Option 3

| | |
|------------|--|
| Nil | Power supply/Output connection cable (2 m) |
| N | None |

* Cable is shipped together, but not connected.

Option 2

| | |
|------------|--|
| Nil | None |
| 4C | Sensor connector (4 pcs.) ZS-28-C |

- * Connector is not connected, but shipped together.
- * This connector cannot be used with the PSE570 series.

Options/Part Nos.

When only optional parts are required, order with the part numbers listed below.

| Description | Part no. | Note |
|---|-------------------------------------|---|
| Panel mount adapter | ZS-26-B | Waterproof seal, Tapping screw: Nominal size 3 x 8L (2 pcs.) included |
| Front protection cover + Panel mount adapter | ZS-26-C | Waterproof seal, Tapping screw: Nominal size 3 x 8L (2 pcs.) included |
| <input type="checkbox"/> 48 conversion adapter * This adapter is used to mount the PSE200A series on the panel fitting of the PSE100 series. | ZS-26-D | Order panel mount adapter separately. |
| Front protection cover | ZS-26-01 | |
| Sensor connector (1 pc. per set) | ZS-28-C ZS-28-CA-4 | For the PSE500 series (Excludes the PSE570 series) For PSE570 series |
| Power supply with M12 connector/Output cable (Made to Order) * For use when using an M12 connector for IO-Link communication | ZS-26-LM12 | |

Multi-channel Digital Sensor Monitor **PSE200A Series**

For pressure switch precautions and specific product precautions, refer to the "Operation Manual" on the SMC website. Click [here](#) for details.

Specifications

| Series | PSE200A | | | | | | | | |
|-------------------------------------|---|---|--|----------------|------------------|--------------------------------------|-------------------|-------------------|------------------|
| Applicable SMC pressure sensor | PSE550 | PSE531 PSE541 PSE561 | PSE533 PSE543 PSE563 PSE573 | PSE532 | PSE564 PSE574 | PSE530 PSE540 PSE560 PSE570 | PSE575 | PSE576 | PSE577 |
| Rated pressure range | 0 to 2 kPa | 0 to -101 kPa | -100 to 100 kPa | 0 to 100 kPa | 0 to 500 kPa | 0 to 1 MPa | 0 to 2 MPa | 0 to 5 MPa | 0 to 10 MPa |
| Display/Set pressure range | -0.2 to 2.1 kPa | 10 to -105 kPa | -105 to 105 kPa | -10 to 105 kPa | -50 to 525 kPa | -0.105 to 1.05 MPa | -0.105 to 2.1 MPa | -0.25 to 5.25 MPa | -0.5 to 10.5 MPa |
| Display/Smallest settable increment | 0.001 kPa | 0.1 kPa | 0.1 kPa | 0.1 kPa | 1 kPa | 0.001 MPa | 0.001 MPa | 0.01 MPa | 0.01 MPa |
| Electrical | Power supply voltage | When used as a switch output device 12 to 24 VDC $\pm 10\%$ with 10% ripple (p-p) or less | | | | | | | |
| | Power supply voltage for sensor ^{*1} | When used as an IO-Link device 18 to 30 VDC, including ripple (p-p) 10% ^{*1} | | | | | | | |
| | Current consumption | 55 mA or less | | | | | | | |
| | Protection | Polarity protection | | | | | | | |
| | Power supply current for sensor ^{*2} | [Power supply voltage] -1.5 V Max. 50 mA (However, the total current for the 4 inputs is 200 mA maximum or less.) | | | | | | | |
| Accuracy | Display accuracy | $\pm 0.5\%$ F.S. ± 1 digit (Ambient temperature of 25 $\pm 3^\circ\text{C}$) | | | | | | | |
| | Repeatability | $\pm 0.1\%$ F.S. ± 1 digit | | | | | | | |
| | Temperature characteristics | $\pm 0.5\%$ F.S. (Reference: 25 $^\circ\text{C}$) | | | | | | | |
| Switch output (S/O mode) | Output type | NPN or PNP open collector output: 5 outputs | | | | | | | |
| | Output mode | Hysteresis mode, Window comparator mode, Error output, Output OFF | | | | | | | |
| | Switch operation | Normal output, Reversed output | | | | | | | |
| | Max. load current | 80 mA | | | | | | | |
| | Max. applied voltage (NPN only) | 30 VDC | | | | | | | |
| | Internal voltage drop (Residual voltage) | 1.5 V or less (at load current of 80 mA) | | | | | | | |
| | Delay time ^{*3} | 5 ms or less, variable from 0 to 60 s/0.01 s increments | | | | | | | |
| | Hysteresis | Variable from 0 ^{*4} | | | | | | | |
| | Protection | Over current protection | | | | | | | |
| | Sensor input | Input type | Voltage input: 1 to 5 VDC (Input impedance: 1 M Ω) | | | | | | |
| Number of inputs | | 4 inputs | | | | | | | |
| Connection method | | e-CON | | | | | | | |
| Protection | | Over voltage protection (up to a voltage of 26.4 VDC) | | | | | | | |
| Auto-shift input ^{*5} | Voltage free input (Reed or Solid state), input for 5 ms or longer, Independently controllable auto-shift function ON/OFF | | | | | | | | |
| Display | Unit ^{*6} | MPa, kPa, Pa, kgf/cm ² , bar, mbar, psi, inHg, mmHg, mmH ₂ O (depends on selected range) | | | | | | | |
| | Display type | LCD | | | | | | | |
| | Number of screens | 3-screen display (Main screen, Sub screen x 2) | | | | | | | |
| | Display color | Main screen: Red/Green, Sub screen: Orange | | | | | | | |
| | Number of display digits | Main screen: 4 digits (7 segments), Sub screen (Left): 4 digits (some digits are 11-segments, 7 segments for other), Sub screen (Right): 5 digits (some digits are 11-segments, 7 segments for other) | | | | | | | |
| Digital filter ^{*7} | Indicator light | Lights up when switch output is turned ON. OUT1, OUT2: Orange | | | | | | | |
| | Response time | Variable from 0 to 30 s/0.01 s increments | | | | | | | |
| Environment | Enclosure | Front face: IP65 (when panel-mounted), Others: IP40 ^{*8} | | | | | | | |
| | Withstand voltage | 1000 VAC for 1 minute between terminals and housing | | | | | | | |
| | Insulation resistance | 50 M Ω or more (500 VDC measured via megohmmeter) between terminals and housing | | | | | | | |
| | Operating temperature range | Operating: 0 to 50 $^\circ\text{C}$, Stored: -10 to 60 $^\circ\text{C}$ (No condensation) | | | | | | | |
| Standards | Operating humidity range | Operating/Stored: 35 to 85% RH (No condensation) | | | | | | | |
| | Marking | CE/UKCA marking | | | | | | | |
| Weight | Body | 51 g (Excludes power supply and output cable) | | | | | | | |
| | Power supply/Output cable | 60 g | | | | | | | |
| Communication (IO-Link mode) | e-CON (1 pc.) | 2 g | | | | | | | |
| | IO-Link type | Device | | | | | | | |
| | IO-Link version | V1.1 | | | | | | | |
| | Communication speed | COM2 (38.4 kbps) | | | | | | | |
| | Configuration file | IODD file ^{*9} | | | | | | | |
| | Minimum cycle time | 4.8 ms | | | | | | | |
| | Process data length | Input data: 10 bytes, Output data: 0 bytes | | | | | | | |
| | On request data communication | Yes | | | | | | | |
| | Data storage function | Yes | | | | | | | |
| | Event function | Yes | | | | | | | |
| Vendor ID | 131 (0 x 0083) | | | | | | | | |

*1 Check the power supply voltage range of the connected sensor.

*2 Over current on DC (+) side and DC (-) side of the sensor input connector results in breakage of the product.

*3 Value without digital filter (at 0 ms)

*4 If the applied pressure fluctuates around the set value, the hysteresis must be set to a value more than the amount of fluctuation, or chattering will occur.

*5 This setting is only possible for the PSE200A/PSE201A.

*6 This setting is only possible for models with the unit selection function. Only MPa, kPa, or Pa is available for models without this function.

*7 The response time indicates when the set value is 90% in relation to the step input.

*8 If □48 conversion adapter is used, it meets IP40.

*9 The configuration file can be downloaded from the SMC website, <https://www.smcworld.com>

* Products with tiny scratches, marks, or display color or brightness variations which do not affect the performance of the product are verified as conforming products.

Cable Specifications

| | | |
|----------------|------------------------------|------------|
| Conductor area | 0.15 mm ² (AWG26) | |
| Insulator | O.D. | 0.9 mm |
| Sheath | Finished O.D. | $\phi 4.8$ |

PSE200A Series

Applicable Pressure Sensors

| Applicable SMC pressure sensor | | | | | Rated pressure range | | | | | | | |
|--------------------------------|--------|--------|--------|--------|----------------------|---------|---------|---------|-------|-------|-------|--------|
| PSE53□ | PSE54□ | PSE550 | PSE56□ | PSE57□ | -100 kPa | 0 | 100 kPa | 500 kPa | 1 MPa | 2 MPa | 5 MPa | 10 MPa |
| PSE531 | PSE541 | — | PSE561 | — | -101 kPa | 0 | | | | | | |
| PSE533 | PSE543 | — | PSE563 | PSE573 | -100 kPa | 100 kPa | | | | | | |
| PSE532 | — | — | — | — | 0 | 100 kPa | | | | | | |
| — | — | — | PSE564 | PSE574 | 0 | 500 kPa | | | | | | |
| PSE530 | PSE540 | — | PSE560 | PSE570 | 0 | 1 MPa | | | | | | |
| — | — | — | — | PSE575 | 0 | 2 MPa | | | | | | |
| — | — | — | — | PSE576 | 0 | 5 MPa | | | | | | |
| — | — | — | — | PSE577 | 0 | 10 MPa | | | | | | |
| — | — | PSE550 | — | — | 0 | 12 kPa | | | | | | |


Internal Circuits and Wiring Examples

PSE20□ A - □□□□

• Input/Output specifications


0

• NPN open collector 5 outputs + Auto-shift 1 input



1

• PNP open collector 5 outputs + Auto-shift 1 input



Internal Circuits and Wiring Examples


PSE20 **A** -

• Input/Output specifications


2

· IO-Link/NPN open collector 1 output + NPN open collector 4 outputs

When used as an IO-Link device



When used as a switch output device



PSE200A Series

Internal Circuits and Wiring Examples


PSE20 A -

• Input/Output specifications


3

· IO-Link/PNP open collector 1 output + PNP open collector 4 outputs


When used as an IO-Link device




When used as a switch output device





Dimensions



Front protection cover + Panel mount adapter



48 conversion adapter + Panel mount adapter





Panel fitting dimensions
 Applicable panel thickness:
 0.5 to 8 mm

PSE200A Series



Function Details

Display examples of the main and sub (set value) screens of each mode. (When 1 MPa range is selected)



Hysteresis mode, Normal output





Hysteresis mode, Reversed output



Window comparator mode, Normal output



Window comparator mode, Reversed output




Function Details

A Auto-preset function (F4)

This function, when selected in the initial setting, calculates and stores the set value from the measured pressure. For example, if this function is used for suction verification, the optimum set value is determined automatically by repeating vacuum and break with the target workpiece several times.

Suction Verification




Formula for Obtaining the Set Value

| P_1 or n_1 | H_1 |
|--|-----------------------|
| $P_1 = A - (A - B) / 4$ $n_1 = B + (A - B) / 4$ | $H_1 = (A - B) / 2 $ |

B Display value fine adjustment function (F6)

Fine adjustment of the indicated value of the pressure sensor can be made within the range of $\pm 5\%$ of the read value. (This eliminates wide variations of the indicated value.)



— Indicated value at the time of shipment
 - - - Adjustable range of display value fine adjustment function

* When the display value fine adjustment function is used, the set pressure value may change ± 1 digit.

C Peak/Bottom value indication function

This function constantly detects and updates the maximum (minimum) pressure when the power is supplied, and allows to hold the maximum (minimum) pressure value.

When the \odot and \ominus buttons are simultaneously pressed for 1 second or longer, while "holding", the held value will be reset.

D Key-lock function

This function prevents operation errors such as accidentally changing setting values.

E Zero-clear function

This function clears and resets the zero value on the display of measured pressure. The indicated value can be adjusted within $\pm 7\%$ F.S. of the pressure at the time of factory shipment. ($\pm 3.5\%$ F.S. for compound pressure)

F Error display function

This function displays error location and content when a problem or error has occurred.

| Error name | Error code | Description | Action |
|-------------------------|------------|--|---|
| Over current error | | The load current applied to the switch output has exceeded the maximum value. *1 indicates the channel with an error. | Turn the power off and remove the cause of the over current. Then supply the power again. |
| Residual pressure error | | During zero-clear operation, pressure over $\pm 7\%$ F.S. is present. Note that the mode is returned to measurement mode automatically 1 second later. The zero-clear range varies by $\pm 1\%$ F.S. due to variation between individual products. | Perform zero-clear operation again after restoring the applied pressure to an atmospheric pressure condition. |
| Applied pressure error | | Supply pressure exceeds the maximum set pressure. | Reset applied pressure to a level within the set pressure range. Check the sensor connection. |
| | | Supply pressure is below the minimum set pressure. A sensor may be disconnected or mis-wired. | |
| System error | | Internal data error | Turn the power off and then on again. If the failure cannot be solved, please contact SMC for investigation. |

If the error cannot be reset after the above measures are taken, or errors other than those above are displayed, please contact SMC for investigation.


Function Details

G Anti-chattering function (Simple setting mode or F1, F2)

A large bore cylinder or ejector consumes a large volume of air during operation and may experience a temporary drop in the supply pressure. This function prevents the detection of such temporary drops in the supply pressure as errors by changing the delay time setting. The delay time can be set in the range of 0.00 to 60.00 [s] in 0.01 [s] increments.

<Principle>

This function averages pressure values measured during the response time set by the user and then compares the average pressure value with the pressure set point value to output the result on the switch.



H Pressure range/Unit selection function (F0)

Pressure range and displayed units can be switched with this function.

| Display/Smallest settable increment | Display unit | Rated pressure range | Display/ Set pressure range | MPa | kPa | Pa | kgf/cm ² | bar | mbar | psi | inHg | mmHg | mmH ₂ O | |
|-------------------------------------|--------------|----------------------|-----------------------------|-------|-------|----|---------------------|-----|------|-------|------|------|--------------------|---|
| | | | | MPa | kPa | Pa | kgf/cm ² | bar | mbar | psi | inHg | mmHg | mmH ₂ O | |
| Applicable SMC pressure sensor | PSE550 | 0 to 2 kPa | -0.2 to 2.1 kPa | / | 0.001 | 1 | / | / | 0.01 | 0.001 | / | / | 0.1 | |
| | PSE531 | 0 to -101 kPa | 10 to -105 kPa | 0.001 | 0.1 | / | / | / | / | 0.01 | 0.1 | 1 | / | |
| | PSE541 | | | | | | | | | | | | | |
| | PSE561 | -100 to 100 kPa | -105 to 105 kPa | 0.001 | 0.1 | / | / | / | / | 0.02 | 0.1 | 1 | / | |
| | PSE533 | | | | | | | | | | | | | |
| | PSE543 | | | | | | | | | | | | | |
| | PSE563 | | | | | | | | | | | | | |
| | PSE573 | 0 to 100 kPa | -10 to 105 kPa | 0.001 | 0.1 | / | / | / | / | 0.01 | / | / | / | |
| | PSE532 | | | | | | | | | | | | | |
| | PSE564 | | | | | | | | | | | | | |
| | PSE574 | 0 to 500 kPa | -50 to 525 kPa | 0.001 | 1 | / | / | / | / | 0.1 | / | / | / | |
| | PSE530 | 0 to 1 MPa | -0.105 to 1.05 MPa | 0.001 | 1 | / | / | / | / | / | 0.1 | / | / | / |
| | PSE540 | | | | | | | | | | | | | |
| PSE560 | | | | | | | | | | | | | | |
| PSE570 | | | | | | | | | | | | | | |
| PSE575 | 0 to 2 MPa | -0.105 to 2.1 MPa | 0.001 | 1 | / | / | / | / | 0.2 | / | / | / | | |
| PSE576 | 0 to 5 MPa | -0.25 to 5.25 MPa | 0.01 | / | / | / | / | / | 1 | / | / | / | | |
| PSE577 | 0 to 10 MPa | -0.5 to 10.5 MPa | 0.01 | / | / | / | / | / | 1 | / | / | / | | |
| - | - | 0 to 1.6 MPa | -0.105 to 1.68 MPa | 0.001 | 1 | / | / | / | / | 0.1 | / | / | / | |
| | | 0 to 20 MPa | -1 to 21 MPa | 0.01 | / | / | / | / | / | 2 | / | / | / | |
| | | 0 to 25 MPa | -1.26 to 26.26 MPa | 0.02 | / | / | / | / | / | 2 | / | / | / | |

I Zero-cut setting (F14)

When the pressure display value is close to zero, this function forces the display to zero.

The range to display zero can be changed within the range of 0.0 to 10.0%.

Example: When the PSE570 (1 MPa range), zero-cut value = 1.0%, 0 is displayed in the range of -9 to 9 kPa.

J Power-saving mode (F80)

Power-saving mode can be selected.

It shifts to power-saving mode automatically when there is no button operation for 30 seconds.

The product is set to normal mode (Power-saving mode is OFF) at the time of factory shipment.

(When in power-saving mode, [ECO] will flash in the sub screen and the operation light will be ON (only when the switch is ON).)

K Setting of security code (F81)

Users can select whether a security code must be entered to release the key lock.

At the time of factory shipment, it is set so that a security code is not required.


Function Details

L Auto-shift function (F5) (This setting is only possible for the PSE200A/PSE201A.)

When there are large fluctuations in the supply pressure, the switch may fail to operate correctly.

This function compensates for such supply pressure fluctuations. It measures the pressure at the time of auto-shift signal input and uses it as the reference pressure to correct the set value on the switch.

Set value correction by auto-shift function



*1 When delay time is 1.5 ms or less

When the auto-shift function is selected, "PS in 000" will be displayed on the sub screen for about 1 second, and the pressure value at that point will be saved as reference value "L_5". Based on the saved reference value, output on-off points controlled by set values*2 such as "P_1", "H_1", "P_2", and "H_2" will also be rectified.

*2 When an output is reversed, output on-off points displayed at "n_1", "H_1", "n_2", and "H_2" will be rectified.

The above is an example in hysteresis mode. On-off points are similarly rectified in window comparator mode. Outputs that enable the auto-shift function can be changed via the settings.

Settable Range for Auto-Shift Input

| Range settings | Settable range |
|-----------------|---------------------|
| 0 to 2 kPa | -2.30 to 2.300 kPa |
| 0 to -101 kPa | 115.0 to -115.0 kPa |
| -100 to 100 kPa | -210 to 210.0 kPa |
| 0 to 100 kPa | -115.0 to 115.0 kPa |
| 0 to 500 kPa | -575 to 575 kPa |
| 0 to 1 MPa | -1.155 to 1.155 MPa |
| 0 to 2 MPa | -2.20 to 2.205 MPa |
| 0 to 5 MPa | -5.50 to 5.50 MPa |
| 0 to 10 MPa | -11.00 to 11.00 MPa |
| 0 to 1.6 MPa | -1.785 to 1.785 MPa |
| 0 to 20 MPa | -22.0 to 22.00 MPa |
| 0 to 25 MPa | -27.5 to 27.50 MPa |

Auto-shift zero

The basic function of auto-shift zero is the same as that of auto-shift. However, it corrects values on the display based on a pressure value of "0", which is set as the reference value when auto-shift function is selected.

M Differential pressure check mode (F0)

Set and display the differential pressure between CH1 - CH2, and CH3 - CH4.

Selected channel is CH1: Differential pressure between CH1 - CH2 can be set and displayed.

Selected channel is CH2: Measurement value of CH2 can be set and displayed.

Selected channel is CH3: Differential pressure between CH3 - CH4 can be set and displayed.

Selected channel is CH4: Measurement value of CH4 can be set and displayed.

N Channel to channel copy function (F95)

Information that can be copied includes the following:

F0 (system setting): Connected range, displayed unit


F1 (OUT1 setting), F3 (digital filter), F4 (auto-preset), F5 (auto-shift setting), F10 (sub-screen setting), F11 (display resolution setting), F14 (zero-cut setting)

When CH1 is copied to CH2, CH3, and CH4, information on OUT1 in CH1 will be copied.

When CH2 (CH3, or CH4) is copied to CH1, information on OUT1 in CH2 (CH3, or CH4) will be copied only to OUT1 in CH1.

* When the channel to channel copy function is used, the copied pressure set value may vary by ± 1 digit.

Example) When copying CH1 to another channel



* Channel can be selected as the copy channel.


PSE200A Series

Function Details

O Channel select function


Pressure value for the selected channel is displayed.

The function setting of each channel is performed on the selected channel.




P Channel scan function


Pressure values for each channel are displayed in turn every 2 seconds.




Safety Instructions

These safety instructions are intended to prevent hazardous situations and/or equipment damage. These instructions indicate the level of potential hazard with the labels of “**Caution**,” “**Warning**” or “**Danger**.” They are all important notes for safety and must be followed in addition to International Standards (ISO/IEC)*1), and other safety regulations.

 **Caution:** **Caution** indicates a hazard with a low level of risk which, if not avoided, could result in minor or moderate injury.

 **Warning:** **Warning** indicates a hazard with a medium level of risk which, if not avoided, could result in death or serious injury.

 **Danger:** **Danger** indicates a hazard with a high level of risk which, if not avoided, will result in death or serious injury.

*1) ISO 4414: Pneumatic fluid power – General rules relating to systems.
ISO 4413: Hydraulic fluid power – General rules relating to systems.
IEC 60204-1: Safety of machinery – Electrical equipment of machines.
(Part 1: General requirements)
ISO 10218-1: Manipulating industrial robots – Safety.
etc.

Warning

1. The compatibility of the product is the responsibility of the person who designs the equipment or decides its specifications.

Since the product specified here is used under various operating conditions, its compatibility with specific equipment must be decided by the person who designs the equipment or decides its specifications based on necessary analysis and test results. The expected performance and safety assurance of the equipment will be the responsibility of the person who has determined its compatibility with the product. This person should also continuously review all specifications of the product referring to its latest catalog information, with a view to giving due consideration to any possibility of equipment failure when configuring the equipment.

2. Only personnel with appropriate training should operate machinery and equipment.

The product specified here may become unsafe if handled incorrectly. The assembly, operation and maintenance of machines or equipment including our products must be performed by an operator who is appropriately trained and experienced.

3. Do not service or attempt to remove product and machinery/equipment until safety is confirmed.

1. The inspection and maintenance of machinery/equipment should only be performed after measures to prevent falling or runaway of the driven objects have been confirmed.
2. When the product is to be removed, confirm that the safety measures as mentioned above are implemented and the power from any appropriate source is cut, and read and understand the specific product precautions of all relevant products carefully.
3. Before machinery/equipment is restarted, take measures to prevent unexpected operation and malfunction.

4. Contact SMC beforehand and take special consideration of safety measures if the product is to be used in any of the following conditions.

1. Conditions and environments outside of the given specifications, or use outdoors or in a place exposed to direct sunlight.
2. Installation on equipment in conjunction with atomic energy, railways, air navigation, space, shipping, vehicles, military, medical treatment, combustion and recreation, or equipment in contact with food and beverages, emergency stop circuits, clutch and brake circuits in press applications, safety equipment or other applications unsuitable for the standard specifications described in the product catalog.
3. An application which could have negative effects on people, property, or animals requiring special safety analysis.
4. Use in an interlock circuit, which requires the provision of double interlock for possible failure by using a mechanical protective function, and periodical checks to confirm proper operation.

Caution

1. The product is provided for use in manufacturing industries.

The product herein described is basically provided for peaceful use in manufacturing industries.
If considering using the product in other industries, consult SMC beforehand and exchange specifications or a contract if necessary.
If anything is unclear, contact your nearest sales branch.

Limited warranty and Disclaimer/ Compliance Requirements

The product used is subject to the following “Limited warranty and Disclaimer” and “Compliance Requirements”.

Read and accept them before using the product.

Limited warranty and Disclaimer

1. The warranty period of the product is 1 year in service or 1.5 years after the product is delivered, whichever is first.*2)
Also, the product may have specified durability, running distance or replacement parts. Please consult your nearest sales branch.
2. For any failure or damage reported within the warranty period which is clearly our responsibility, a replacement product or necessary parts will be provided.
This limited warranty applies only to our product independently, and not to any other damage incurred due to the failure of the product.
3. Prior to using SMC products, please read and understand the warranty terms and disclaimers noted in the specified catalog for the particular products.

*2) Vacuum pads are excluded from this 1 year warranty.

A vacuum pad is a consumable part, so it is warranted for a year after it is delivered.
Also, even within the warranty period, the wear of a product due to the use of the vacuum pad or failure due to the deterioration of rubber material are not covered by the limited warranty.

Compliance Requirements

1. The use of SMC products with production equipment for the manufacture of weapons of mass destruction (WMD) or any other weapon is strictly prohibited.
2. The exports of SMC products or technology from one country to another are governed by the relevant security laws and regulations of the countries involved in the transaction. Prior to the shipment of a SMC product to another country, assure that all local rules governing that export are known and followed.

Caution

SMC products are not intended for use as instruments for legal metrology.

Measurement instruments that SMC manufactures or sells have not been qualified by type approval tests relevant to the metrology (measurement) laws of each country. Therefore, SMC products cannot be used for business or certification ordained by the metrology (measurement) laws of each country.

Safety Instructions

Be sure to read the “Handling Precautions for SMC Products” (M-E03-3) and “Operation Manual” before use.